

EXCITATION OF RESONATORS BY ELECTRON BEAMS

E.G.Bessonov^{†† 1}

Yukio Shibata[†], Satoshi Sasaki[†], Kimihiro Ishi[†], Mikihiro Ikezawa[†]

[†] *RISM, Tohoku University, Japan* ^{††} *Lebedev Phys. Inst. RAS, Moscow, Russia*

Abstract

Elements of a little-known vector theory of open resonators and experiments on excitation of a fundamental mode with transverse and longitudinal polarization in such resonators are discussed.

PACS number(s): 41.60.Cr. **Keywords:** Open resonators, Longitudinal fundamental TEM mode, polarization.

The propagation of electromagnetic waves in vacuum is described by Maxwell equations. More simple wave equations for electromagnetic fields coupled by conditions $\text{div}\vec{E} = \text{div}\vec{H} = 0$, or for the potentials $\vec{A}$, φ introduced by the equations $\vec{H} = \text{rot}\vec{A}$, $\vec{E} = -\text{grad}\varphi - (1/c)(\partial\vec{A}/\partial t)$ and coupled by a gauge condition can be used for a simplified solution of electrodynamic problems. The following simplification is using the electric and magnetic Hertz vectors $\vec{\Pi}^e$, $\vec{\Pi}^m$. They are introduced by $\vec{A} = (1/c)(\partial\vec{\Pi}^e/m)/(\partial t)$, $\varphi = -\text{div}\vec{\Pi}^e/m$. The so defined potentials $\vec{A}$ and φ will satisfy both the gauge and Maxwell equations. In this case, the electric and magnetic field strengths are

$$\begin{aligned}\vec{E} &= \text{grad}\text{div}\vec{\Pi}^e - \frac{1}{c^2}\frac{\partial^2\vec{\Pi}^e}{\partial t^2} - \frac{1}{c}\frac{\partial}{\partial t}\text{rot}\vec{\Pi}^m, \\ \vec{H} &= \frac{1}{c}\frac{\partial}{\partial t}\text{rot}\vec{\Pi}^e + \text{grad}\text{div}\vec{\Pi}^m - \frac{1}{c^2}\frac{\partial^2\vec{\Pi}^m}{\partial t^2}.\end{aligned}\quad (1)$$

The vectors $\vec{\Pi}^e$ and $\vec{\Pi}^m$ fulfil the wave equation $\square\vec{\Pi}^{e/m} = 0$. We can identify the solution of the scalar wave equation $\square U = 0$ with one component of vectors $\vec{\Pi}^e$ or $\vec{\Pi}^m$ (e.g. $\vec{\Pi}^e = \vec{e}_x \cdot 0 + \vec{e}_y \cdot 0 + \vec{e}_z \cdot U$, $\vec{\Pi}^m = 0$). Substituting the vector in (1) we find the electromagnetic field strengths. Then we can

identify the same solution U by another component of the Hertz vector, equate the rest components to zero, and calculate the other electromagnetic field strengths. After going through all the compositions of components we obtain a set of six different electromagnetic wave modes [1].

The monochromatic light beams of a limited diameter related to the resonator modes can be written in the form $U = V(x, y, z)e^{i(kz - \omega t)}$, where $V(x, y, z)$ is the function of a coordinate slowly varying in comparison with $\exp[i(kz - \omega t)]$. In a paraxial approximation $|\partial^2 V/\partial z^2| \ll 2k|\partial V/\partial z|$, $k = \omega/c$ this form is described by the equation $2ki\partial V/\partial z + \partial^2 V/\partial x^2 + \partial^2 V/\partial y^2 = 0$. The solution of this equation by the method of separation of variables in the cylindrical coordinates, where $V(x, y, z) = G(u)\Phi(\phi)\exp[ikr^2/2q(z)]\cdot\exp[iS(z)]$, $r = \sqrt{x^2 + y^2}$, and ϕ are the cylindrical coordinates, $u = r/w(z)$, has the form

$$\begin{aligned}V(r, \phi, z) &= \\ \frac{C}{w(z)} \left(\frac{r}{w(z)}\right)^m \left(\frac{\sin m\phi}{\cos m\phi}\right) L_n^m \left(\frac{2r^2}{w^2(z)}\right) \\ \exp \left\{ \frac{ikr^2}{2q(z)} - i(m+2n+1)\text{arctg} \frac{z}{Z_R} \right\},\end{aligned}\quad (2)$$

where L_n^m are the Lagerian polynomials ($L_0^0(\xi) =$

¹ Corresponding author. bessonov@sgi.lpi.msk.su.

$1, L_1^0 = 1 - \xi, \dots$; $Z_R = \pi w_0^2/\lambda$, the Rayleigh length; $\lambda = 2\pi c/\omega$, the wavelength; $C = \text{constant}$; $1/q(z) = 1/R(z) + i\lambda/\pi w^2$; $R(z) = z[1 + (Z_R/z)^2]$, the radius of the wave front of Gaussian beam; $w^2(z) = w_0^2[1 + (z/Z_R)^2]$; $w(z)$, the radius of the beam, and $w_0(z)$ the radius of the beam waist.

The compositions 1) $\Pi_x^e = U(x, y, z)$, $\Pi_y^e = \Pi_z^e = 0$ or 2) $\Pi_x^e = 0$, $\Pi_y^e = U(x, y, z)$, $\Pi_z^e = 0$ or 3) $\Pi_x^e = 0$, $\Pi_y^e = 0$, $\Pi_z^e = U(x, y, z)$ together with the conditions $\vec{\Pi}^m = 0$, $\partial^2 V/\partial x_i \partial x_k \ll k\partial V/\partial x_i \ll k^2 V$ lead to the field strengths

$$\begin{aligned} E_x^{e,1} &\simeq -H_y^{e,1} \simeq k^2 U(x, y, z), & E_y^{e,1} &\simeq H_x^{e,1} \simeq 0, \\ E_z^{e,1} &= 2ikx \left[\frac{1}{w^2(z)} + \frac{ik}{R(z)} \right] U(x, y, z), \\ H_z^{e,1} &= 2iky \left[\frac{1}{w^2(z)} + \frac{ik}{R(z)} \right] U(x, y, z) \\ E_x^{e,3} &= -H_y^{e,3} = 2ikx \left[\frac{1}{w^2(z)} + \frac{ik}{R(z)} \right] U(x, y, z), \\ E_y^{e,3} &= -H_x^{e,3} = -2iky \left[\frac{1}{w^2(z)} + \frac{ik}{R(z)} \right] U(x, y, z), \\ E_z^{e,3} &= 2ik \left[\frac{w_0^2 z}{w^2(z) Z_R^2} \left(\frac{2r^2}{w^2(z)} - 1 \right) - \frac{ikr^2}{2R^2(z)} \right. \\ &\quad \left. \left(1 - \frac{Z_R^2}{z^2} \right) - \frac{iw_0^2}{w^2 Z_R} \right] U(x, y, z), & H_z^3 &= 0, \end{aligned} \quad (3)$$

where the upper superscripts show the composition of the electric Hertz vector corresponding to the transverse (x,y) and longitudinal (z) polarizations. The second case can be received from the first one by substitution of the variable x by y , and vice versa. The field strengths received from the magnetic Hertz vector are $\vec{E}' = -\vec{H}$, $\vec{H}' = \vec{E}$.

In the first case, the Gaussian beam has mainly the transverse field components, where $E_z^{e,1}(r=0) = 0$. In the third case, the field components are compatible by the value ($E_z^{e,1}(r=0) \neq 0$) [1], [2]. These are the fundamental transversely and longitudinally polarized $TEM_{00}^{e,1}$ and $TEM_{00}^{e,3}$ (TM_{01}) modes, accordingly. The $TEM_{00}^{e,3}$ modes can be excited by the transition radiation emitted on mirrors of open resonators by electrons that are homogeneously moving along their axes. Such an excitation was probably observed in the experiments

published in [3]. Previous experiments on excitation of open resonators were done under conditions when the electron trajectories were directed either at some angle to the axis of a resonator [4], or along caustics of the fundamental mode of a resonator [5], where the fundamental $TEM_{00}^{e,1}$ modes had not a longitudinal component of the electric field strength at the open resonator axis. Electron beams of finite transverse dimensions moving along the axes of open resonators can excite non-efficiently higher modes like $TEM_{10}^{e,1,2}$ having small longitudinal components near the axes of resonators [3, b].

Excitation of the $TEM_{00}^{e,3}$ modes is possible at even harmonics of undulator radiation in free-electron lasers using the flat undulators with a high deflecting parameters when the amplitudes of longitudinal oscillations are high. Radiation stored at this mode in supercavity can be used for laser driven acceleration in vacuum as well.

We thank Prof. A.N.Oraevsky and Prof. Ming Xie for the discussion of this paper.

References

- [1] A.N.Oraevsky, *Gaussian Beams and Optical resonators*, Nova Science Publ., Inc. Commack, 1995 (translated from Proc. Lebedev Phys. Inst., v. 187, Nauka, Moscow, 1988).
- [2] a) L.W.Davis, G.Patsakos, Optics Letters, Vol. 6, No 1, p.22, 1981; b) S.R.Seshadri, J. Opt. Soc. Am., A, v. 15, No 10, 1998.
- [3] a) Yukio Shibata, Kimihiro Ishi, Shuichi Ono, et al., Phys. Rev. Lett., 1997, v.78, No 14, 2740; b) Nucl. Instr., Meth. B 145 (1998), 49.
- [4] E.Brannen, V.Sells, H.R.Froelich, Proc. IEEE, **55**, No 5, 717 (1967).
- [5] V.M.Chernenko, Elektronika Bolschich moschnostei, Collection of papers, Vol. 6, Moscow, Nauka, 1969, p.135.